

# IPG130 GENSET

Generating Set Powered By  Perkins 

Image for illustration purposes only

## Output Ratings

Generating Set Model	Prime Power	Standby Power
1500rpm, 50 Hz/ 400V	108KWe / 135KVA	120KWe / 150KVA
1800rpm, 60 Hz / 440V	122KWe/152KVA	135KWe/169KVA

## Genset Specifications

Engine Make & Model	Perkins 1106A-70TG1
Origin	UK
Alternator Type	LSA44.2VS75-UCI274G
Control Panel	DIGITAL DEAP SEA
Circuit Breaker Type	3 Pole MCCB
Water Cooling System	
Mechanical Governor	
Electrical Stop Solenoid, Energized to Run	
Compact Size	

Fuel System	50%	75%	100%
1500rpm, 50 Hz	15.9	22.7	30.2
1800rpm, 60Hz	18.0	26.5	35.2

\*Prime Power (l/hr)

## Engine Technical Data


No. of Cylinders / Alignment	6 In Line
Cycle	4 Stroke
Aspiration	turbocharged
Injection	Direct
Bore, mm	105
Stroke, mm	135
Displacement, l	7.0
Compression Ratio	18.2:1
Starting	12V Electric
Alternators, Amps	12V/ 65A

## Alternator Technical Data

No. of Bearings	Single Bearing
Insulation System	Class H
Excitation	Self Excited
Voltage Regulator	SX460
Protection	IP23
Temperature Rise, °C	125
Regulation	±1.0%
No. of Phases	3
No. of Poles	4

## Dimensions & Weights

Length(m)	Width(m)	Height(m)	Weight(kg)	Tank Capacity(L)
2.70	0.90	1.5	1400	200



## RATING GUIDELINES

**PRIME POWER** rating corresponds to ISO Standard Power for continuous operation. It is applicable for supplying electrical power at variable load for an unlimited number of hours instead of commercially purchased power. A 10% overload capability for governing purpose is available for this rating.

**MAXIMUM STANDBY POWER** rating corresponds to ISO Standard Fuel Stop Power. It is applicable for supplying standby electrical power at variable load in areas with well established electrical networks in the event of normal utility power failure. No overload capability is available for this rating. **1 hp = 1 kW x 1.36**

# IPG130 GENSET

Generating Set Powered By  Perkins **STAMFORD**

**LEROY**  
**SOMER**

Performances	1500rpm	1800rpm
Alternator Efficiency	91.7%	91.7%
<b>Engine Power</b>		
Prime Power, KWm(hp)	118.3(158.6)	133.5(143.2)
Standby Power, KWm(hp)	131.4(176)	148.4(199)
<b>Alternator</b>		
Prime Power, KWe	112	134

Lubrication System	1500rpm	1800rpm
Oil Consumption (l/hr)	0.2% of fuel consumption	
Oil Sump Capacity, l	14.9	
Oil System Capacity Include Filters, l	18	

Cooling System	1500rpm	1800rpm
Heat Radiation from Engine and Alternator, Power KW	25.9	27
Heat Rejection to Coolant and Lube Oil at Standby Power, KW	82	92
Radiator Cooling Air Flow, m <sup>3</sup> /min (cfm)	228.6(8073)	234(8264)
Coolant Capacity, l	21	

Intake & Exhaust System	1500rpm	1800rpm
Air Flow Combustion at Standby Power, m <sup>3</sup> /min(cfm)	8.1(280)	11.5(405)
Heat Rejection Exhaust at Standby Power, KW	-	-
Exhaust Gas Temperature at Standby °C	561	526
Max Allowable Back Pressure in Exhaust Line, Kpa	6.0	6.0
Exhaust Gas Flow at Standby Power, m <sup>3</sup> /min(cfm)	22.7(800)	29.7(1050)

Accessories	
Oil Drain	Anti-Vibration Pads
Stainless Steel Flexible	Fuel Tank Base Frame for 8hrs
Standard Silencer	Battery disconnect switch

## Control Panel Readings

- AC volts, AC currents, DC volts, frequency, rpm, hour counter, power factor.
- Low oil pressure, high water temperature, boost pressure and temperature, KW, KWh, KVA, KVAR
- Oil pressure, low oil level, high oil temperature
- DC alternator failure, over speed, over crank (Fail to start), over under voltage, over under current, any sensor failure
- Low coolant level - Configurable inputs & outputs
- Upgradable for GSM network connection, Signal SMS messages.

## Optional Equipment

- **Engine**
  - Coolant heater
  - Oversize batteries
  - Extra fuel pre-filter water separator
  - Battery Disconnect Switch
  - Electrical Governor
- **Alternator**
  - permanent magnet generator (PMG)
  - Upgrade to 3 phase sensing AVR
  - Qadrature droop kit
  - Anti-condensation heater
  - Air inlet filters
- **General**
  - Upgrade to modular controller for paralleling
  - Upgrade to 4 pole circuit breaker
  - Battery charger
  - Automatic transfer switch
  - Fuel level switch High / Low for alarm and control
  - Fuel transfer pump Automatic / Manual
  - Residential grade silencer
  - Weather protective and acoustic enclosure.

## Spare Parts Kit (Optional)

Genuine - Perkins

Oil filter, full flow	(1)
Fuel filter	(2)
Air filter	(1)
Fan belt set	(1)
Alternator belt set	(1)

## General Information

### Documentation

Engine instruction book-English  
Alternator manual- English  
Wiring diagram

### Warranty

One year or 1000 thousand hours whichever elapsed first against all defects in material / or workmanship, subject to the terms and conditions of the Manufacturer's warranty.