



# IPG9 GENSET

Generating Set Powered By  Perkins **STAMFORD**  
**LEROY SOMER**

Image for illustration purposes only

## Output Ratings

Generating Set Model	Prime Power	Standby Power
1500rpm, 50 Hz / 400V	7KWe / 9KVA	8KWe / 10KVA
1800rpm, 60 Hz / 440V	-	-

## Genset Specifications

Engine Make & Model	Perkins 403A-11G1
Origin	UK
Alternator Type	LSA37M6 - PI044E
Control Panel	Digital Deap Sea
Circuit Breaker Type	3 Pole MCB
Water Cooling System	
Mechanical Governor	
Electrical Stop Solenoid, Energized to Run	
Compact Size	

Fuel System	50%	75%	100%
1500rpm, 50 Hz	1.7	2.3	3.0
1800rpm, 60Hz	-	-	-

\*Prime Power (l/hr)

## Engine Technical Data


No. of Cylinders /Alignment	3 In Line
Cycle	4 Stroke
Aspiration	Naturally
Injection	Indirect
Bore, mm	77.0
Stroke, mm	81.0
Displacement,l	1.13
Compression Ratio	23:1
Starting	12V Electric
Alternators, Amps	12V/15A

## Alternator Technical Data

No. of Bearings	Single Bearing
Insulation System	Class H
Excitation	Self Excited
Voltage Regulator	AS480
Protection	IP23
Temperature Rise, °C	125
Regulation	±1.0%
No. of Phases	3
No. of Poles	4

## Dimensions & Weights

Length(m)	Width(m)	Height(m)	Weight(kg)	Tank Capacity(L)
1.30	0.52	1.25	375	38



## RATING GUIDELINES

**PRIME POWER** rating corresponds to ISO Standard Power for continuous operation. It is applicable for supplying electrical power at variable load for an unlimited number of hours instead of commercially purchased power. A10 % overload capability for governing purpose is available for this rating.

**MAXIMUM STANDBY POWER** rating corresponds to ISO Standard Fuel Stop Power. It is applicable for supplying standby electrical power at variable load in areas with well established electrical networks in the event of normal utility power failure. No overload capability is available for this rating. 1 hp = 1 kW x 1.36

# IPG9 GENSET

Generating Set Powered By  Perkins

**STAMFORD**  
**LEROY**  
**SOMER**

## Control Panel Reading

Performances	1500rpm	1800rpm
<b>Alternator Efficiency</b>	80.5%	-
<b>Engine Power</b>		
Prime Power, KWm(hp)	8.4(11.3)	-
Standby Power, KWm(hp)	9.2(12.4)	-
<b>Alternator</b>		
Prime Power, KWe	8	-

- AC volts, AC currents, DC volts, frequency, rpm, hour counter, power factor.
- Low oil pressure, high water temperature, boost pressure and temperature, KW, KWh, KVA, KVAR
- Oil pressure, low oil level, high oil temperature
- DC alternator failure, over speed, over crank (Fail to start), over under voltage, over under current, any sensor failure
- Low coolant level - Configurable inputs&outputs
- Upgradable for GSM network connection, Signal SMS messages.

Lubrication System	1500rpm	1800rpm
<b>Oil Consumption (l/hr)</b>	0.1% of fuel consumption	-
<b>Oil Sump Capacity, l</b>	4.4	-
<b>Oil System Capacity Include Filters, l</b>	4.9	-

## Optional Equipment

- **Engine**
  - Coolant heater
  - Oversize batteries
  - Extra fuel pre-filter water separator
  - Battery Disconnect Switch
  - Electrical Governor
- **Alternator**
  - Excitation Boost System (EBS)
  - Upgrade to 3 phase sensing AVR
  - Qadrature droop kit
  - Anti-condensation heater
  - Air inlet filters
- **General**
  - Upgrade to modular controller for paralleling
  - Upgrade to 4 pole circuit breaker
  - Battery charger
  - Automatic transfer switch
  - Fuel level switch High / Low for alarm and control
  - Fuel transfer pump Automatic / Manual
  - Residential grade silencer
  - Weather protective and acoustic enclosure.

Cooling System	1500rpm	1800rpm
<b>Heat Radiation from Engine and Alternator, Power KW</b>	2.5	-
<b>Heat Rejection to Coolant and Lube Oil at Standby Power, KW</b>	9.5	-
<b>Radiator Cooling Air Flow, m<sup>3</sup>/min (cfm)</b>	24(848)	-
<b>Coolant Capacity, l</b>	5.2	-

Intake & Exhaust System	1500rpm	1800rpm
<b>Air Flow Combustion at Standby Power, m<sup>3</sup>/min(cfm)</b>	0.7(25)	-
<b>Heat Rejection Exhaust at Standby Power, KW</b>	8	-
<b>Exhaust Gas Temperature at Standby °C</b>	420	-
<b>Max Allowable Back Pressure in Exhaust Line, Kpa</b>	10.2	-
<b>Exhaust Gas Flow at Standby Power, m<sup>3</sup>/min(cfm)</b>	1.8(64)	-

## Spare Parts Kit (Optional) Genuine - Perkins

Oil filter, full flow	(1)
Fuel filter	(1)
Air filter	(1)
Fan belt set	(1)
Alternator belt set	(1)

## Accessories

Oil Drain	Anti-Vibration Pads
Stainless Steel Flexible Standard Silencer	Fuel Tank Base Frame for 8hrs

## General Information

### Documentation

Engine instruction book-English  
Alternator manual- English  
Wiring diagram

### Warranty

One year or 1000 thousand hours whichever elapsed first against all defects in material / or workmanship, subject to the terms and conditions of the Manufacturer's warranty.