

ICG810 GENSET

Generating Set Powered By



LEROY SOMER
STAMFORD

Output Ratings

Generating Set Model	Prime Power	Standby Power
1500rpm, 50 Hz / 400V648kWe / 810KVA	720KWe / 900KVA	
1800rpm, 60 Hz / 440V727KWe / 909KVA	800KWe/1000KVA	

Genset Specifications

Engine Make & Model Cummins QSK23G3

Origin USA

Alternator Type UCI634G

Control Panel Digital Deap Sea

Circuit Breaker Type 3 Pole MCCB

Water Cooling System

Mechanical Governor

Electrical Stop Solenoid, Energized to Run

Compact Size

Fuel System	50%	75%	100%
1500rpm, 50 Hz	85.00	121.0	161.0
1800rpm, 60Hz	97.00	139.0	189.0

*Prime Power (l/hr)

RATING GUIDELINES

PRIME POWER rating corresponds to ISO Standard Power for continuous operation. It is applicable for supplying electrical power at variable load for an unlimited number of hours instead of commercially purchased power. A10 % overload capability for governing purpose is available for this rating.

MAXIMUM STANDBY POWER rating corresponds to ISO Standard Fuel Stop Power. It is applicable for supplying standby electrical power at variable load in areas with well established electrical networks in the event of normal utility power failure. No overload capability is available for this rating. 1 hp = 1 kW x 1.36

Engine Technical Data


No. of Cylinders / Alignment	6/ In Line
Cycle	4 - Stroke
Aspiration	Turbocharged
Injection	Direct
Bore, mm	170
Stroke, mm	170
Displacement, l	23.1
Compression Ratio	16.0:1
Starting	24V Electric
Alternators, Amps	24V/35A

Alternator Technical Data

No. of Bearings	Single Bearing
Insulation System	Class H
Excitation	PMG
Voltage Regulator	MX321
Protection	IP23
Temperature Rise, °C	125
Regulation	±0.5%
No. of Phases	3
No. of Poles	4

Dimensions & Weight

Length(m)	Width(m)	Height(m)	Weight(kg)	Tank Capacity(L)
4.45	1.7	2.15	6350	N/A



ICG500GENSET

Generating Set Powered By



STAMFORD
LEROY
SOMER

Performances	1500rpm	1800rpm
Alternator Efficiency	94.5%	94.5%
Engine Power		
Prime Power, KWm(hp)	682(915)	776(1040)
Standby Power, KWm(hp)	739(991)	856(1149)
Alternator		
Prime Power, KWe	648	710

Lubrication System	1500rpm	1800rpm
Oil Consumption (l/hr)		0.03
Oil Sump Capacity, l		95
Oil System Capacity Include Filters, l		103

Cooling System	1500rpm	1800rpm
Heat Radiation from Engine and Alternator, Power KW	71	85
Heat Rejection to Coolant and Lube Oil at Standby Power, KW	222	269
Radiator Cooling Air Flow, m ³ /s	13.5	16.6
Coolant Capacity, l		156.5

Intake & Exhaust System	1500rpm	1800rpm
Air Flow Combustion at Standby Power, m ³ /min(cfm)	53.3(1280)	67.9(1290)
Heat Rejection Exhaust at Standby Power, KW	570	656
Exhaust Gas Temperature at Standby °C	543	514
Max Allowable Back Pressure in Exhaust Line, Kpa	10.2	10.2
Exhaust Gas Flow at Standby Power, m ³ /min(cfm)	147.8(5218)	183.4(6475)

Accessories

Oil Drain Pump	Anti-Vibration Pads
Stainless Steel Flexible	Genuine Oil
Genuine Oil	Coolant 'Ready Mix'
Genuine Coolant	Fuel Tank Base Frame for 8hrs
Standard Silencer	

Control Panel Readings

- AC volts, AC currents, DC volts, frequency, rpm, hour counter, power factor.
- Low oil pressure, high water temperature, boost pressure and temperature, KW, KWh, KVA, KVAR
- Oil pressure, low oil level, high oil temperature
- DC alternator failure, over speed, over crank (Fail to start), over under voltage, over under current, any sensor failure
- Low coolant level - Configurable inputs & outputs
- Upgradable for GSM network connection, Signal SMS messages.

Optional Equipment

- **Engine**
 - Coolant heater
 - Oversize batteries
 - Extra fuel pre-filter water separator
 - Battery Disconnect Switch
 - Electrical Governor
- **Alternator**
 - Excitation Boost System (EBS)
 - Upgrade to 3 phase sensing AVR
 - Quadrature droop kit
 - Anti-condensation heater
 - Air inlet filters
- **General**
 - Upgrade to modular controller for paralleling
 - Upgrade to 4 pole circuit breaker
 - Battery charger
 - Automatic transfer switch
 - Fuel level switch High / Low for alarm and control
 - Fuel transfer pump Automatic / Manual
 - Residential grade silencer
 - Weather protective and acoustic enclosure.

Spare Parts Kit (Optional)

Genuine - Cummins

Oil filter	(2)
Fuel filter	(2)
Air filter	(1)
Fan belt set	(1)
Alternator belt set	(1)

General Information

Documentation

Engine instruction book-English
Alternator manual- English
Wiring diagram

Warranty

One year or 1000 thousand hours whichever elapsed first against all defects in material / or workmanship, subject to the terms and conditions of the Manufacturer's warranty.

IMG HEAD OFFICES
IMG Bldg, Mazraa area Beirut-Lebanon
Phone: +961 (1) 311737 Mobile: +961 (03) 059 995
Website: www.img-lb.com